



Clicky PeopleCounter

Datasheet



Document history

Version	Date	Comment	Author
1.0	14-02-2018	Initial release	RG
1.1	20-02-2018	Updated product name	RG
1.2	10-04-2018	Added LoRa Alliance certification	RG
1.3	29-08-2019	Updated document	NvG

Clickey PeopleCounter

Compact, LoRaWAN specification 1.0.2 compliant, Class A, 868MHz / 915MHz, battery powered, people counter. Ideally suited to create 'Smart Meeting Rooms' and 'Smart buildings'.

The onboard sensors register:

- People entering a room
- People leaving a room
- People lingering in a doorway
- People passing by in a hallway



Specifications

Functionality	Multisensor LoRaWAN Class A device
Power supply	2x 1,5V Lithium, size AA batteries (not included)
Battery life	12+ months (typical; 24 x per day reporting)
Operating temperature	0 °C to +50 °C
Sensors	PIR
Antenna	Integrated 3,0 dB
Chipset	Semtech (SX1276) + STM (STM32L)
Processor	STM32L151
Water resistance	Indoor use only
Dimensions	(LxBxH) 100 mm x 74 mm x 48 mm
Weight	111 grams
Certifications	CE
Controls	Dashboard on International Clickey Cloud Portal (ICCP)
Portal Data storage	3 months rolling, CSV-file download and graphs

Disclaimer

Use and proper functioning of Clickey devices is subject to local LoRa network coverage and internet availability. Do not use for critical situations. CLICKEY solutions is not liable for any damages resulting from the use of our products.

Customer support

Users of Clickey hardware and/or Cloud portal can receive assistance by contacting their sales representative or by contacting technical support at support@clickey.eu.

Copyright © 2019 CLICKEY solutions

All rights reserved. This paper or any portion thereof may not be reproduced or used in any manner whatsoever without the express written permission of CLICKEY solutions.

Information contained in this publication regarding device specifications is provided only for your convenience and may be superseded by updates.

It is your responsibility to ensure that your application meets with your specifications. CLICKEY solutions disclaims all liability arising from this information and its use. Use of CLICKEY solutions devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless CLICKEY solutions from any and all damages, claims, suits, or expenses resulting from such use.